




1. Insert the mounting ring into the duct 'E' from the face of the ceiling.
2. Fasten the mounting ring into the duct using the holes at the rear of the mounting ring.
3. Insert the SDR into the mounting ring. Rotate the SDR until it locks into the place. The "U" tabs should fit around the tightening screws.
4. Tighten using a Phillips screw driver.

Model	C	D	E	O
SDR-06	13/16	6	2 1/4	7 1/2
SDR-08	13/16	8	2 1/4	9 1/2
SDR-10	1	10	2 1/4	11 7/8
SDR-12	1	12	2 1/4	13 7/8
SDR-14	2	14	2 7/8	17 7/8



UNLESS OTHERWISE SPECIFIED:		NAME	DATE	
DIMENSIONS ARE IN INCHES TOLERANCES: ± 1/32" FRACTIONAL ANGULAR: MACH ± BEND ± TWO PLACE DECIMAL ± THREE PLACE DECIMAL ±		DRAWN	M.H. 10/06/14	
INTERPRET GEOMETRIC TOLERANCING PER:		CHECKED		SDR Installation Instruction
MATERIAL		ENG APPR.		
FINISH		MFG APPR.		SIZE DWG. NO. REV
DO NOT SCALE DRAWING		Q.A.		A
		COMMENTS:		SCALE: 1:12 WEIGHT: SHEET 1 OF 1